



A22-308 ADDRESS TABLE				Function 03 Read Holding Registers												
Name		Address		Range		Explain		initial		Unit	Read/Write	Note				
		Decimal	Hexadecimal	High Byte	Low Byte	High Byte	Low Byte	" A "	" 2 "							
Model & Company	0	0000	Constatnt Ascii of Model & Company			Model & Company name		" A "	" 2 "		R	"A " "2" Ascii Code				
	1	0001						" Y "	" - "		R	"Y" (1 or 2) "-" Ascii Code				
	2	0002						" 5 "	nn		R	"5" "nn" Ascii Code or "3" "nn" Ascii Code				
	3	0003						" F "	" N "		R	"F" "N" Ascii Code				
	4	0004					RX TX Couner	" P "	0		R	"P" Ascii Code 0				
Version	5	0005	00 to 256	00 to 256	Hardware Version		Software Version		HW	SW		R	Hardware & Software Version			
Date Number	6	0006	(00D - 99D)H (01D - 12D)L		Year		Month		YM			R				
Seial Number	7	0007	0 to 65535		Serial Number				SN			R				
Password	8	0008	0 to 9999		Password				1234			R				
ID Address	9	0009		1 to 247	Device Address RS485 Communication				0	247		R	Default MODBUS ID address is : 1			
Baud Rate	10	000A	00h to 07h		Baud Rate of RS-485 Communication		0005H	Bit/S	R	Baud Rate	00h	300				
											01h	600				
											02h	1200				
											03h	2400				
											04h	4800				
											05h	9600				
											06h	14400				
											07h	19200				
Parity & Stop bit	11	000B	01h to 05h		Parity & Stop Bit Communication		0004H		R	Parity & Stop bit	00h	None parity 1 Stop bit				
											01h	None parity 2 Stop bit				
											02h	Odd parity 1 Stop bit				
											03h	Odd parity 2 Stop bit				
											04h	Even parity 1 Stop bit				
											05h	Even parity 2 Stop bit				
Automatic Turn Off HORN	12	000C	1800 to 0 second Down Timer		Non Critical horn off timer				600		Sec	R				
	13	000D	1801 to 0 second Down Timer		Critical horn off timer				600		Sec	R				
Fault Counter & ISA Sequence	14	000E	0 to 24	85 , 90 , 165 , 170 , 53 , 60	Alarm or Fault Counter	ISA Sequence	0	85		R	ISA-2C	55h	85			
											ISA-A	5Ah	90			
											ISA-F2A	A5h	165			
											ISA-F3M	Aah	170			
											ISA-F3A	35h	53			
											Simple window	3Ch	60			
Alarm system Status	15	000F	00h to FFh	00h to FFh	Alarm System Status					R	Critical Horn Status	bit 0	0	Relay OFF	1	Relay ON
											Non Critical Horn Status	bit 1	0	Relay OFF	1	Relay ON
											N/A	bit 2	0	N/A	1	N/A
											Flash Fast Status	bit 3	0	Flash OFF	1	Flash ON
											Flash Normal Status	bit 4	0	Flash OFF	1	Flash ON
											Flash Slow Status	bit 5	0	Flash OFF	1	Flash ON
											Lamp Test Status	bit 6	0	Normal Status	1	Lamp test Status
											Wiring Ok	bit 7	0	Sync Wiring Error	1	Sync Wiring OK
											N/A	bit 8	0	N/A	1	N/A
											N/A	bit 9	0	N/A	1	N/A



A22-308 ADDRESS TABLE						Function 03 Read Holding Registers											
Name		Address		Range		Explain		initial		Unit	Read/Write	Note					
		Decimal	Hexadecimal	High Byte	Low Byte	High Byte	Low Byte										
												N/A	bit 10	0	N/A	1	N/A
												N/A	bit 11	0	N/A	1	N/A
												N/A	bit 12	0	N/A	1	N/A
												HornOff PB Exist	bit 13	0	NO	1	YES
												Horn Test Requier	bit 14	0	NO	1	YES
												Internal Horn ON/OFF	bit 15	0	OFF	1	ON
Channel 1	Status	16	0010	5 to 65535		Bit pattern Status for Channel 1		00h	40h		R	Input	bit 0	0	Input channel LOW	1	Input channel HIGH
Channel 2	Status	17	0011	5 to 65535		Bit pattern Status for Channel 2		00h	40h		R	D Input	bit 1	0	Debounce input LOW	1	Debounce input HIGH
Channel 3	Status	18	0012	5 to 65535		Bit pattern Status for Channel 3		00h	40h		R	Alarm in	bit 2	0	Input fault deactive	1	Input fault active
Channel 4	Status	19	0013	5 to 65535		Bit pattern Status for Channel 4		00h	40h		R	Fst Alarm	bit 3	0	No First Alarm	1	First Alarm
Channel 5	Status	20	0014	5 to 65535		Bit pattern Status for Channel 5		00h	40h		R	Nack.	bit 4	0	No alarm	1	No acknowledge alarm
Channel 6	Status	21	0015	5 to 65535		Bit pattern Status for Channel 6		00h	40h		R	Ack.	bit 5	0	Reset Alarm	1	Acknowledge alarm
Channel 7	Status	22	0016	5 to 65535		Bit pattern Status for Channel 7		00h	40h		R	NO/NC	bit 6	0	NC channel	1	NO channel
Channel 8	Status	23	0017	5 to 65535		Bit pattern Status for Channel 8		00h	40h		R	Cr/NCr	bit 7	0	Non critical channel	1	Critical channel
Channel 1	ON Delay Timer	40	0028	5 to 65535		ON Delay Setting Channel 1		6	mSec		R	Status	bit 8	0	Alarm or Fault	1	Signal (ON / OFF)
Channel 2	ON Delay Timer	41	0029	5 to 65535		ON Delay Setting Channel 2		6	mSec		R	reserve	bit 9	0	For future define	1	For future define
Channel 3	ON Delay Timer	42	002A	5 to 65535		ON Delay Setting Channel 3		6	mSec		R	reserve	bit 10	0	For future define	1	For future define
Channel 4	ON Delay Timer	43	002B	5 to 65535		ON Delay Setting Channel 4		6	mSec		R	Alarm Priority Number bit 0	bit 11	Alarm Priority Number bit 0 to 4 (0 to 31)			
Channel 5	ON Delay Timer	44	002C	5 to 65535		ON Delay Setting Channel 5		6	mSec		R	Alarm Priority Number bit 1	bit 12				
Channel 6	ON Delay Timer	45	002D	5 to 65535		ON Delay Setting Channel 6		6	mSec		R	Alarm Priority Number bit 2	bit 13				
Channel 7	ON Delay Timer	46	002E	5 to 65535		ON Delay Setting Channel 7		6	mSec		R	Alarm Priority Number bit 3	bit 14				
Channel 8	ON Delay Timer	47	002F	5 to 65535		ON Delay Setting Channel 8		6	mSec		R	Alarm Priority Number bit 4	bit 15				
Channel 1	OFF Delay Timer	64	0040	5 to 65535		OFF Delay Setting Channel 1		30	mSec		R						
Channel 2	OFF Delay Timer	65	0041	5 to 65535		OFF Delay Setting Channel 2		30	mSec		R						
Channel 3	OFF Delay Timer	66	0042	5 to 65535		OFF Delay Setting Channel 3		30	mSec		R						
Channel 4	OFF Delay Timer	67	0043	5 to 65535		OFF Delay Setting Channel 4		30	mSec		R						
Channel 5	OFF Delay Timer	68	0044	5 to 65535		OFF Delay Setting Channel 5		30	mSec		R						
Channel 6	OFF Delay Timer	69	0045	5 to 65535		OFF Delay Setting Channel 6		30	mSec		R						
Channel 7	OFF Delay Timer	70	0046	5 to 65535		OFF Delay Setting Channel 7		30	mSec		R						
Channel 8	OFF Delay Timer	71	0047	5 to 65535		OFF Delay Setting Channel 8		30	mSec		R						
Channel 1	Color ON state	88	0058	0	1 to 7	0	Color ON State of Channel 1	0	7		R	RED	1				
Channel 2	Color ON state	89	0059	0	1 to 7	0	Color ON State of Channel 2	0	7		R	GREEN	2				
Channel 3	Color ON state	90	005A	0	1 to 7	0	Color ON State of Channel 3	0	7		R	YELLOW	3				
Channel 4	Color ON state	91	005B	0	1 to 7	0	Color ON State of Channel 4	0	7		R	BLUE	4				
Channel 5	Color ON state	92	005C	0	1 to 7	0	Color ON State of Channel 5	0	7		R	MAGENTA	5				
Channel 6	Color ON state	93	005D	0	1 to 7	0	Color ON State of Channel 6	0	7		R	CYAN	6				
Channel 7	Color ON state	94	005E	0	1 to 7	0	Color ON State of Channel 7	0	7		R	WHITE	7				
Channel 8	Color ON state	95	005F	0	1 to 7	0	Color ON State of Channel 8	0	7		R						
Channel 1	Color OFF state	112	0070	0	0 to 7	0	Color OFF State of Channel 1	0	7		R	BLACK	0	Custom Order			
Channel 2	Color OFF state	113	0071	0	0 to 7	0	Color OFF State of Channel 2	0	7		R	RED	1				
Channel 3	Color OFF state	114	0072	0	0 to 7	0	Color OFF State of Channel 3	0	7		R	GREEN	2				
Channel 4	Color OFF state	115	0073	0	0 to 7	0	Color OFF State of Channel 4	0	7		R	YELLOW	3				



A22-308 ADDRESS TABLE						Function 03 Read Holding Registers																					
Name		Address		Range		Explain		initial		Unit	Read/Write	Note															
		Decimal	Hexadecimal	High Byte	Low Byte	High Byte	Low Byte																				
Channel 5	Color OFF state	116	0074	0	0 to 7	0	Color OFF State of Channel 5	0	7		R	BLUE	4	سفارش خاص													
Channel 6	Color OFF state	117	0075	0	0 to 7	0	Color OFF State of Channel 6	0	7		R	MAGENTA	5														
Channel 7	Color OFF state	118	0076	0	0 to 7	0	Color OFF State of Channel 7	0	7		R	CYAN	6														
Channel 8	Color OFF state	119	0077	0	0 to 7	0	Color OFF State of Channel 8	0	7		R	WHITE	7														
Channel 1	ISA Sequence	136	0088	0	85 , 90 , 165 , 170 , 53 , 60	0	ISA Sequence of Channel 1	0	85		R	Custom Order سفارش خاص															
Channel 2	ISA Sequence	137	0089	0		0	ISA Sequence of Channel 2	0	85		R																
Channel 3	ISA Sequence	138	008A	0		0	ISA Sequence of Channel 3	0	85		R					ISA-2C	55h	85									
Channel 4	ISA Sequence	139	008B	0		0	ISA Sequence of Channel 4	0	85		R					ISA-A	5Ah	90									
Channel 5	ISA Sequence	140	008C	0		0	ISA Sequence of Channel 5	0	85		R					ISA-F2A	A5h	165									
Channel 6	ISA Sequence	141	008D	0		0	ISA Sequence of Channel 6	0	85		R					ISA-F3M	Aah	170									
Channel 7	ISA Sequence	142	008E	0		0	ISA Sequence of Channel 7	0	85		R					ISA-F3A	35h	53									
Channel 8	ISA Sequence	143	008F	0		0	ISA Sequence of Channel 8	0	85		R																
Channel 1	Input status Indication	160	00A0	0	01b or 10b	0	Double Point Input of Channel 1	0	2		R	Comment	bit 1	bit 0													
Channel 2	Input status Indication	161	00A1	0	01b or 10b	0	Double Point Input of Channel 2	0	2		R	Intermediate Position	0	0													
Channel 3	Input status Indication	162	00A2	0	01b or 10b	0	Double Point Input of Channel 3	0	2		R	Normal Position ON	0	1													
Channel 4	Input status Indication	163	00A3	0	01b or 10b	0	Double Point Input of Channel 4	0	2		R	Normal Position OFF	1	0													
Channel 5	Input status Indication	164	00A4	0	01b or 10b	0	Double Point Input of Channel 5	0	2		R	Faulty Position	1	1													
Channel 6	Input status Indication	165	00A5	0	01b or 10b	0	Double Point Input of Channel 6	0	2		R																
Channel 7	Input status Indication	166	00A6	0	01b or 10b	0	Double Point Input of Channel 7	0	2		R																
Channel 8	Input status Indication	167	00A7	0	01b or 10b	0	Double Point Input of Channel 8	0	2		R																
Channel 1 - 8	Input status Indication (Refer to function5 address 4)	184	00B8	5555h to AAAAh		Double Point Input of Channel 1 - 8 (2bit for each channel)		55h	55h		R	b15 In8	b14 In8	b13 In7	b12 In7	b11 In6	b10 In6	b9 In5	b8 In5	b7 In4	b6 In4	b5 In3	b4 In3	b3 In2	b2 In2	b1 In1	b0 In1
Channel 1 - 8	Input status Indication (Refer to function5 address 4)	187	00BB	AAAAh to 5555h		Double Point Input of Channel 1 - 8 (2bit for each channel)		AAh	AAh		R	b15 In8	b14 In8	b13 In7	b12 In7	b11 In6	b10 In6	b9 In5	b8 In5	b7 In4	b6 In4	b5 In3	b4 In3	b3 In2	b2 In2	b1 In1	b0 In1
Channel 1 - 16	Input status Indication (Refer to function5 address 4)	190	00BE	0b or 1b	0b or 1b	Single Point Input of Channel 1 - 16 (1bit for each channel)		0	0		R	b15 In16	b14 In15	b13 In14	b12 In13	b11 In12	b10 In11	b9 In10	b8 In9	b7 In8	b6 In7	b5 In6	b4 In5	b3 In4	b2 In3	b1 In2	b0 In1
Beep Time		192	0070	10 to 200		Beep Time (mSec) Setting		30	mSec		R/W																
V. Fast Flash Time		193	0071	200-800		Very Fast Flash Per Minute Setting		500	/ minute		R/W																
Fast Flash Time		194	0072	100-600		Fast Flash Per Minute Setting		270	/ minute		R/W																
Normal Flash Time		195	0073	20-150		Normal Flash Per Minute Setting		54	/ minute		R/W																
Slow Flash Time		196	0074	10-100		Slow Flash Per Minute Setting		15	/ minute		R/W																
P. Flash Time		197	0075	100-800		Programming Flash Per Minute Setting		300	/ minute		R/W																
CPU LAST ERROR		198	0076			Use By Manufacturer		OXFFFF																			
Cpu Error Counter		199	0077	0 to 65535		Cpu Error Counter		0			R																
Programming exit counter		200	0078	0 to 65535		Programming exit counter		0			R																
Power ON Reset Counter		201	0079	0 to 65535		Power ON Reset Counter		0			R																
External Reset Counter		202	007A	0 to 65535		External Reset Counter		0			R																
Brown Out Reset Counter		203	007B	0 to 65535		Brown Out Reset Counter		0			R																
Watchdog Reset Counter		204	007C	0 to 65535		Watchdog Reset Counter		0			R																
EEPROM Crash Counter		205	007D	0 to 65535		EEPROM Crash Counter		0			R																
Factory Reset Counter		206	007E	1 to 65535		Factory Reset Counter		0			R																

A22-308 ADDRESS TABLE				Function 05 Write Single Coil						
Name	Address		Range	Explain		initial	Unit	Read/Write	Note	
	Decimal	Hexadecimal		High Byte	Low Byte					Preset Single Coil ON
Horn Off P.B. exist	1	0001	ON or OFF	Horn Off P.B. exist (3 or 4 Push Botton action)		ON		W	YES	NO
Horn Test require	2	0002	ON or OFF	Horn Test require (Horn test in Lamp test function require?)		ON		W	YES	NO
Internal Horn	3	0003	ON or OFF	Internal Horn ON / OFF (Internal Buzzer)		ON		W	ON	OFF
Selecting Indication of Input status	4	0004	ON or OFF	Indication " <u>non Acknowledged Alarm Channel</u> " or <u>Input Channel</u>		ON		W	Indication non Acknowledged Alarm channel	Indication Input channel
									نمایش خطا تا زمانی ادامه خواهد داشت که توسط کاربر آکنالچ (Acknowledge) شود. در این حالت، حتی در صورت رفع خطا از روی دستگاه، پیام خطا تا زمان آکنالچ کاربر باقی خواهد ماند. The error remains displayed until it is acknowledged by the user. In this mode, the error message will persist even if the actual error condition on the device has already been resolved	نمایش خطا تنها تا زمانی ادامه خواهد داشت که خطا به صورت واقعی به دستگاه اعمال شود. با برطرف شدن خطا، نمایش آن نیز متوقف می شود. The error is displayed only as long as the error is actually applied to the device. Once the error is cleared, the display will automatically clear
Horn Off P.B.	85	0055	ON	Press Horn Off Push Botton		N/A		W	YES	N/A
Acknowledge P.B.	90	005A	ON	Press Acknowledge Push Botton		N/A		W	YES	N/A
Reset P.B.	165	00A5	ON	Press Reset Push Botton		N/A		W	YES	N/A
Reset Priority P.B.	163	00A3	ON	Press Reset Priority Push Botton		N/A		W	YES	N/A
Lamp Test P.B.	170	00AA	ON	Press Lamp Test Push Botton		N/A		W	YES	N/A
Dimmer Down P.B.	53	0035	ON	Decrease LEDs Light		N/A		W	YES	N/A
Dimmer Up P.B.	58	003A	ON	Increase LEDs Light		N/A		W	YES	N/A

A22-308 ADDRESS TABLE					Function 06 Write Single Register												
Name	Address		Range		Explain		Initial	Unit	Read/Write	Note							
	Decimal	Hexadecimal	High Byte	Low Byte	High Byte	Low Byte						HEX	DEC				
Push Button Command	2	0002	0		0	Push Button Command			W	Horn Off P.B.	0055	85					
										Acknowledge P.B.	005A	90					
										Reset P.B.	00A5	165					
										Reset Priority P.B.	00A3	163					
										Lamp Test P.B.	00AA	170					
										Dimmer Down P.B.	0035	53					
										Dimmer Up P.B.	003A	58					
ISA Sequence Setting	3	0003	0	85 , 90 , 165 , 170 , 53 , 60	0	ISA Sequence Setting			W	ISA-2C	0055	85					
										ISA-A	005A	90					
										ISA-F2A	00A5	165					
										ISA-F3M	00AA	170					
										ISA-F3A	0035	53					
										Simple window	003C	60					
Automatic Turn Off HORN	4	0004	0 to 1800 second Down Timer		Non Critical horn off timer		600	Sec	W								
	5	0005	0 to 1800 second Down Timer		Critical horn off timer		600	Sec	W								
ID Address	7	0007		1 to 247	Device Address RS485 Communication		0	247		W	Change the MODBUS ID is Available in PROGRAMMING MODE only& @ ID address : 255						
Baud Rate	10	000A	00h to 07h		Baud Rate of RS-485 Communication	0005H	Bit/S	R\W	Baud Rate	00h	300						
										01h	600						
										02h	1200						
										03h	2400						
										04h	4800						
										05h	9600						
										06h	14400						
										07h	19200						
Parity & Stop bit	11	000B	01h to 05h		Parity & Baud Rate Communication	0004H		R/W	Parity & Stop bit	00h	None parity 1 Stop bit						
										01h	None parity 2 Stop bit						
										02h	Odd parity 1 Stop bit						
										03h	Odd parity 2 Stop bit						
										04h	Even parity 1 Stop bit						
										05h	Even parity 2 Stop bit						
Pass Word	12	000C	0 to 9999		Pass Word		1234		W								
Date Number	13	000D	(00D - 99D)H (01D - 12D)L		Year	Month	YM		W								
Seial Number	14	000E	0 to 65535		Serial Number		SN		W								

A22-308 ADDRESS TABLE					Function 16 Write Multiple Registers										
Name	Address		Register Address		Explain		Channel Number	Unit	Read/Write	Note					
	Decimal	Hexadecimal	Decimal	Hexadecimal	High Byte	Low Byte						High Byte			Low Byte
Input Logic , Urgent Satatus & Alarm or Signal Input Setting All channels (Range are limited same as side table)	1	0001	1	0001	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	1		W	Each Register Pattern	DEC	HEX		DEC	HEX
			2	0002	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	2			Non Critical - Normaly OPEN	85	55	لطفا اعداد را به صورت اعمال Hex بفرمایید. Please apply the numbers in Hex .format	170	AA
			3	0003	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	3			Non Critical - Normaly CLOSE	85	55			
			4	0004	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	4			Critical - Normaly OPEN	170	AA			
			5	0005	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	5			Critical - Normaly CLOSE	170	AA			
			6	0006	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	6			Signal Lamp - Normaly OPEN	90	5A			
			7	0007	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	7			Signal Lamp - Normaly CLOSE	90	5A			
			8	0008	Critical/Non Critical/Signal Lamp	Normaly OPEN / CLOSE	8								
On Delay Timer Setting All channels (5 to 65000mSec.)	2	0002	1	0001	ON Delay Timer Setting		1	mSec.	W	لطفا توجه داشته باشید که حتما در Function 16 Write Multiple Registers باید در تعداد کل پنجره های آلارم داده وارد شود. یعنی مثلا در اینجا که دستگاه شما 8 پنجره است حتما باید همه ی 8 پنجره عدد وارد شود و اگر فقط بخواهید تعداد 4 پنجره را مقدار دهی کنید با خطا مواجه میشوید. همچنین برای تنظیمات بحرانی و غیر بحرانی و همچنین نرمالی این و نرمالی کلوز بهتر است دستگاه مستر خود را به صورت اعداد Hex تنظیم کنید و سپس طبق جدول فوق عدد مورد نظر را برای بیت های پر ارزش، جهت تنظیم حالت بحرانی و غیر بحرانی و یا لامپ سیگنال وارد نمایید و سپس در سمت بیت های کم ارزش مقدار نرمالی این و نرمالی کلوز را بنویسید. برای مثال برای تنظیم پنجره شماره ی 3 به حالت بحرانی و نرمالی کلوز از ترکیب زیر استفاده میکنیم. 0xAA55 در اینجا بیت پر ارزش AA (تنظیم حالت بحرانی)است و بیت کم ارزش 55 (تنظیم نرمالی کلوز)است					
			2	0002	ON Delay Timer Setting		2	mSec.							
			3	0003	ON Delay Timer Setting		3	mSec.							
			4	0004	ON Delay Timer Setting		4	mSec.							
			5	0005	ON Delay Timer Setting		5	mSec.							
			6	0006	ON Delay Timer Setting		6	mSec.							
			7	0007	ON Delay Timer Setting		7	mSec.							
			8	0008	ON Delay Timer Setting		8	mSec.							
Off Delay Timer Setting All channels (5 to 65000mSec.)	3	0003	1	0001	OFF Delay Timer Setting		1	mSec.	W						
			2	0002	OFF Delay Timer Setting		2	mSec.							
			3	0003	OFF Delay Timer Setting		3	mSec.							
			4	0004	OFF Delay Timer Setting		4	mSec.							
			5	0005	OFF Delay Timer Setting		5	mSec.							
			6	0006	OFF Delay Timer Setting		6	mSec.							
			7	0007	OFF Delay Timer Setting		7	mSec.							
			8	0008	OFF Delay Timer Setting		8	mSec.							
Colour Setting for all channels	4	0004	1	0001	0	ON State Window Color Setting	1		W	RED	1				
			2	0002	0	ON State Window Color Setting	2			GREEN	2				
			3	0003	0	ON State Window Color Setting	3			YELLOW	3				
			4	0004	0	ON State Window Color Setting	4			BLUE	4				
			5	0005	0	ON State Window Color Setting	5			MAGENTA	5				
			6	0006	0	ON State Window Color Setting	6			CYAN	6				
			7	0007	0	ON State Window Color Setting	7			WHITE	7				



			8	0008	0	ON State Window Color Setting	8					
OFF Colour Setting for all channels	5	0005	1	0001	0	OFF State Window Color Setting	1	mSec.	W	BLACK	0	Custom Order سفارش خاص
			2	0002	0	OFF State Window Color Setting	2	mSec.		RED	1	
			3	0003	0	OFF State Window Color Setting	3	mSec.		GREEN	2	
			4	0004	0	OFF State Window Color Setting	4	mSec.		YELLOW	3	
			5	0005	0	OFF State Window Color Setting	5	mSec.		BLUE	4	
			6	0006	0	OFF State Window Color Setting	6	mSec.		MAGENTA	5	
			7	0007	0	OFF State Window Color Setting	7	mSec.		CYAN	6	
			8	0008	0	OFF State Window Color Setting	8	mSec.		WHITE	7	
ISA Sequence for all channels	6	0006	1	0001	0	ISA Sequence Setting	1	mSec.	W	Custom Order سفارش خاص		
			2	0002	0	ISA Sequence Setting	2	mSec.				
			3	0003	0	ISA Sequence Setting	3	mSec.				
			4	0004	0	ISA Sequence Setting	4	mSec.				
			5	0005	0	ISA Sequence Setting	5	mSec.				
			6	0006	0	ISA Sequence Setting	6	mSec.				
			7	0007	0	ISA Sequence Setting	7	mSec.				
			8	0008	0	ISA Sequence Setting	8	mSec.				